

# Create/edit an arming supervision notification

## GoSafer Security Knowledge Base

*This operational reference is organized for GoSafer Security customers and staff. Alarm.com product names are retained where required for technical accuracy.*

## Overview

An arming supervision notification can notify users if the system has not been armed by a certain time.

|                            |                        |
|----------------------------|------------------------|
| <b>Platform</b>            | App + Web              |
| <b>Content type</b>        | How-to / Configuration |
| <b>Source last updated</b> | 2025-06-04             |

## Procedure

### To create an arming supervision notification using the Alarm.com app

1. Log in to the Alarm.com app.
2. Tap [Menu].
3. Tap Notifications.
4. Tap [Settings].
5. Tap [Add].

6. Tap Create Your Own.
7. Tap Arming Supervision.

Name the new notification rule.

## In Send an Arming Reminder if the system is NOT armed, select one of the following

At a specific time to enter a desired time.

When selected people cross a Geo-Fence to select the desired Geo-Devices.

In On the selected days, tap to select either At All Times or Only During the Following Times to define specific times.

1. Tap Add.
2. Tap to select the entries in the address book to be notified.

## If a contact is not listed

1. Tap Add Contact to add a new address book entry.
2. Enter the new contact's information, then tap Add Contact.
3. Tap Close.

**Note:** To remove recipients, tap [Close] to remove the desired notification recipient.

1. Verify the notification is configured with the correct settings.
2. Tap Save.

## To create an arming supervision notification using the GoSafer Security

# customer portal (powered by Alarm.com)

1. Log in to the GoSafer Security customer portal (powered by Alarm.com).
2. Click Notifications.
3. Click New Notification.
4. Click Arming Supervision.

Name the new notification rule.

## In Send an Arming Reminder if the system is NOT armed, select one of the following

At a specific time to enter a desired time.

When selected people cross a Geo-Fence to select the desired Geo-Devices.

In On the selected days, click to select either At All Times or Only During the Following Times to define specific times.

## To choose notification recipients, click Add.

1. Click to select the entries in the address book to be notified.

## If a contact is not listed

1. Click New to add a new address book entry.
2. Enter the new contact's information, then click Add Contact.
3. Click Close.

# Note: To remove recipients, tap [Close] to remove the desired notification recipient.

1. Verify the notification is configured with the correct settings.
2. Click Save.

## Source and support

For GoSafer Security assistance, visit [gosaferssecurity.com](https://gosaferssecurity.com).

Original Alarm.com reference:  
[https://answers.alarm.com/Customer/Website\\_and\\_App/Commercial/Commercial\\_Notifications/Create\\_edit\\_an\\_arming\\_supervision\\_notification](https://answers.alarm.com/Customer/Website_and_App/Commercial/Commercial_Notifications/Create_edit_an_arming_supervision_notification)

Always verify safety, installation, compatibility, and current UI details against the original manufacturer documentation before operational use.

---

Revision #1

Created 2026-09-01 00:29:52 UTC by Jerdenn Calag

Updated 2026-09-01 00:29:52 UTC by Jerdenn Calag